

Template Guidebush System Selection Chart

IMPORTANT: Check the make and model of your router in column 1. Where possible, always order the Leigh adaptors and template guidebushes (indicated in red), which are specially designed for use on Leigh jigs. Leigh also sells other manufacturer's adaptors and template guidebushes (indicated in green). All others must be purchased from the router manufacturer's own distributor. **NOTE: If your router is not listed here, visit leighjigs.com for a complete, up-to-date list of routers.**

1 ROUTER MAKER	2 ROUTER MODEL	3 LEIGH OR ROUTER MAKER'S ADAPTOR NO.	4 7/16" OUTSIDE DIAMETER GUIDE BUSH NO.	5 5/8" OUTSIDE DIAMETER GUIDE BUSH NO.▼	6 METHOD OF ATTACHMENT	7 WORKS WITH LEIGH VGS
AXMINSTER WHITE	AW635R	No adaptor required	711	716	Screws incl. w/router	YES
	AW127R	Adaptor supplied w/router	711	716	Screws incl. w/router	YES
BLACK & DECKER	All Professional, HD 1250, RP400K	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES
	6200	720673-00	711TP or e-Bush	716TP	2 screws req'd. 249412-20	YES
	SR100, 7AEE, KW780 series	No adaptor required	711	716	Screws incl. w/router	YES
BOSCH	90140, 90098, 90088	No adaptor required	82855	82854	Screws included	NO
	90085, 90150, 90300, 90303, 90305, 91264		82859	82864	Screws included	NO
	1600, 1601, 1602, 1603, 1604, 1606, B1350	2 610 906 290	711TP or e-Bush	716TP	Threaded nut included	YES
	1613, 1613EVS, 1613AEVS, 1614, 1614EVS, 1617, 1617EVS, 1618EVS, 1619EVS, B1450	No adaptor required if using RA Template Guides	RA1107	RA1113	No screws required	YES
	POF800ACE, POF1100AE, GOF900ACE, GOF900CE, GOF1200, GOF1300ACE, GOF2000CE, GMF1400	RA1100 required for 711TP, 716TP and VGS	711TP or e-Bush	716TP	Threaded nut included	YES
1611, 1611EVS, 1615, 1615EVS, B1550, GOF1600, GOF1700ACE	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES	
CMT	1E	702R*	711, 711TP or e-Bush	716 or 716TP	◆	YES
CRAFTSMAN (SEARS)	All non-plunge models	No adaptor required	5-piece set from Sears USA: Order no.0925973 or 3-piece set from Sears Canada: Order no.0900970704		Screws incl. w/set	NO
	135275070 Plunge Other plunge models	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES
DEWALT	DW610, DW616, DW618	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES
	DW613	No adaptor required	711	716	Screws incl. w/router	YES
	DW614, DW615, DW621, DW624, DW625 and DW626	North America Only Adaptor supplied w/router	711TP or e-Bush	716TP	Threaded nut included	YES
	DW621K and DW626 outside N. America	706	711	716	◆	YES
	DW625 Type 1, 2, 3, 5 outside N. America	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	DW625 Type 4 outside N. America, DW625EK	702R*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	OF15, OF15E, OF97, OF97E	706	711	716	◆	YES
MOF68, MOF69, MOF96, MOF96E	No adaptor required	711	716	Screws incl. w/router	YES	
MOF131, MOF177 Type 1, 2 & 3	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES	
MOF177 Type 4, MOF177EK	702R*	711, 711TP or e-Bush	716 or 716TP	◆	YES	
2720, 2721, 3328	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES	
3303, 3304	E09600 or 761 270-00	711TP or e-Bush	716TP	Threaded nut included	YES	
3337, 3338, 3339	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES	
FEIN	RT1800	Adaptor supplied w/router	711TP or e-Bush	716TP	◆	YES
FESTOOL	OF1E, OF2E, OF650, OF900E, OF1000, OF1010E	704	711TP	716TP	Threaded nut included	YES
	OF2000, OF2000E	705	711	716	◆	YES
	OF1400 North America Only OF1400 Outside North America	Adaptor supplied w/router 493566	711TP or e-Bush 711TP or e-Bush	716TP 716TP	Threaded nut included Threaded nut included	YES YES
FLEX	All	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES
FREUD	FT2000, FT2200	703*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	FT1700	FT1100	711TP or e-Bush	716TP	Threaded nut included	YES
HITACHI	TR8, TR12, FM8, M8, M12 Series	325211 or 703*	711TP or e-Bush	716TP	Threaded nut included	YES
	M12VC, KM12SC, KM12VC	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES
MAFELL	LO65E	702* ■	711, 711TP or e-Bush	716 or 716TP	◆	YES
MAKITA	3600, 3606, 3608, 3612, 3612B, 3612BR, 3612C N. America, 3620, 3621	703*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	3612C Europe Qk. Fit Base	Contact your National Leigh distributor				
	3601B	321 493-1	711TP or e-Bush	716TP	Threaded nut included	YES
	RP0910, RP1110C	706	711	716	◆	YES
RF1100, RF1101, RD1100, RD1101, RP1101	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES	
METABO	OF1612, OFE1812	704	711TP	716TP	Threaded nut included	YES
MILWAUKEE	5615, 5616, 5619	49-54-1040	711TP or e-Bush	716TP	Threaded nut included	YES
	5625	49-54-1026	711TP or e-Bush	716TP	Threaded nut included	YES
	5670	No adaptor required	711TP or e-Bush	716TP	Threaded nut included	YES
PERLES	OF808 Series, OFE 6990	No adaptor required	711	716	Screws incl. w/router	YES
PORTER CABLE (ROCKWELL)	All	No adaptor required or adaptor supplied w/router	711TP or e-Bush	716TP	Threaded nut included	YES
POWER DEVIL	All	No adaptor required	711	716	Screws incl. w/router	YES
RIDGID	R2930	704	711TP	716TP	Threaded nut included	YES
RYOBI	R30, R50, R150, R151, RE155, R500, R501, R502	703*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	R600, R601, RE600, RE601	702*	711, 711TP or e-Bush	716 or 716TP	◆	YES
	R160, R161, R162, R165, R170, R175, RE175, R180, R180PL, R181, R185	706	711	716	◆	YES
SKIL	1823 or 1835	91803	711TP or e-Bush	716TP	Threaded nut included	YES
	All others	No adaptor required	11592	71021	Nut 11587	NO
	SK1810, 1815, 1820, 1825	RAS140	711TP or e-Bush	716TP	Threaded nut included	YES
TREND (FELLISATI)	T5	No adaptor required	711	716	Screws incl. w/router	YES
	T9	Adaptor supplied w/router				
TRITON	TRC001, TRA001	TGA006 (or 704)	711TP	716TP	Threaded nut included	YES
	MOF001	TRA359	711TP or e-Bush (or 711TP only)	716TP	Threaded nut included	YES
WEGOMA	OF850 Series	No adaptor required	711	716	Screws incl. w/router	YES

◆ Guidebush mounting screws are provided with adaptor and adaptor mounting screws are provided with router. ▼ 5/8" O.D. guidebushes are used only with 1/2" shank router bits. ■ MAFELL – Rework the adaptor slightly. ✦ Leigh Adaptors 702, 702R, and 703 require a small lug to be "drilled out" to use the e-Bush. Note: Ideal barrel depth is 1/4" to 9/32" (6mm to 8mm) below the router base. Other manufacturers' guidebushes may require careful cutting to length. All Leigh bushes have 5/16" long barrels.